

# ASCII CONTROL CODE CHART

b7 b6 b5 BITS b4 b3 b2 b1	0 0		0 1		1 0		1 1									
	0	1	0	1	0	1	0	1								
	CONTROL				SYMBOLS NUMBERS				UPPER CASE				LOWER CASE			
0 0 0 0	0	16	32	48	64	80	96	112	NUL	DLE	SP	0	@	P	'	p
0 0 0 1	1	17	33	49	65	81	97	113	SOH	DC1	!	1	A	Q	a	q
0 0 1 0	2	18	34	50	66	82	98	114	STX	DC2	"	2	B	R	b	r
0 0 1 1	3	19	35	51	67	83	99	115	ETX	DC3	#	3	C	S	c	s
0 1 0 0	4	20	36	52	68	84	100	116	EOT	DC4	\$	4	D	T	d	t
0 1 0 1	5	21	37	53	69	85	101	117	ENQ	NAK	%	5	E	U	e	u
0 1 1 0	6	22	38	54	70	86	102	118	ACK	SYN	&	6	F	V	f	v
0 1 1 1	7	23	39	55	71	87	103	119	BEL	ETB	'	7	G	W	g	w
1 0 0 0	8	24	40	56	72	88	104	120	BS	CAN	(	8	H	X	h	x
1 0 0 1	9	25	41	57	73	89	105	121	HT	EM	)	9	I	Y	i	y
1 0 1 0	10	26	42	58	74	90	106	122	LF	SUB	*	:	J	Z	j	z
1 0 1 1	11	27	43	59	75	91	107	123	VT	ESC	+	;	K	[	k	{
1 1 0 0	12	28	44	60	76	92	108	124	FF	FS	,	<	L	\	l	
1 1 0 1	13	29	45	61	77	93	109	125	CR	GS	-	=	M	]	m	}
1 1 1 0	14	30	46	62	78	94	110	126	SO	RS	.	>	N	^	n	~
1 1 1 1	15	31	47	63	79	95	111	127	SI	US	/	?	O	_	o	DEL

LEGEND:

dec	CHAR
hex      oct	

Victor Eijkhout  
 Dept. of Comp. Sci.  
 University of Tennessee  
 Knoxville TN 37996, USA